

ADJ ENCORE BURST 100IP - DMX TRAITS

CHANNEL					DMX VALUES	FUNCTION
1 CH	2 CH	3 CH	4 CH	5CH		
1	1	1	1	1	000 - 255	Master Dimmer , 0% to 100%
	2	2	2	2	000 - 255	Dimmer Fine , 0% to 100%
		3	3	3		Shutter and Strobing
					000 - 031	Shutter Closed (LED Off)
					032 - 063	Shutter Open (LED On)
					064 - 095	Strobe Effect, slow to fast
					096 - 127	Shutter Open (LED On)
					128 - 159	Pulse Effect in Sequences
					160 - 191	Shutter Open (LED On)
					192 - 223	Random Strobe Effect, slow to fast
					224 - 255	Shutter Open (LED On)
			4	4		Dim Modes
					000 - 020	Standard
					021 - 040	Stage
					041 - 060	TV
					061 - 080	Architectural
					081 - 100	Theatre
					101 - 120	Stage 2
					121 - 140	Dimmer Speed, fast to slow, 0.1s to 10s
					141 - 255	Default to unit setting
				5		Dim Curves
					000 - 020	Square
					021 - 040	Linear
					041 - 060	Inv. Squa
					061 - 080	S. Curve
					081 - 255	No Function