

ELIMINATOR CENTERDROID - DMX TRAITS

CHANNEL 22Ch	DMX VALUES	FUNCTION
1	000-255	X-axis motor travel , 0°-540° travel positioning
2	000-255	X-axis motor speed , speed from fast to slow
3		Center Effect Lens motor
	000-127	0°-360°stroke positioning
	128-191	Rotate clockwise from fast to slow
	192-255	Rotate counterclockwise from slow to
4	000-255	Travel of y-axis motor 1 , 0°-303°
5	000-255	Travel of y-axis motor 2 , 0°-303°
6	000-255	Travel of y-axis motor 3 , 0°-303°
7	000-255	Travel of y-axis motor 4 , 0°-303°
8	000-255	Travel of y-axis motor 5 , 0°-303°
9	000-255	Travel of y-axis motor 6 , 0°-303°
10	000-255	Total dimming , 0 -100%
11		Strobe / Shutter
	000-031	Shutter Closed (LEDs OFF)
	032-063	Shutter OPEN (LEDS ON)
	064-095	Strobe effect slow to fast
	096-127	Shutter OPEN(LEDS ON)
	128-159	Pulse effect in sequences
	160-191	Shutter OPEN(LEDS ON)
	192-223	Random strobe effect slow to fast
	224-255	Shutter OPEN(LEDS ON)
12	000-255	Cel Red Dimmer - red dimming , 0 -100%
13	000-255	Cel Green Dimmer - green dimming , 0 -100%
14	000-255	Cel Blue Dimmer - blue dimming , 0 -100%
15	000-255	Cel White Dimmer - white dimming , 0 -100%
16	000-255	Beam red dimming , 0 -100%
17	000-255	Beam green dimming , 0 -100%
18	000-255	Beam blue dimming , 0 -100%
19	000-255	Beam white dimming , 0 -100%
20		Red laser
	000-015	no stroboscopic
	016-249	speed from slow to fast
	250-255	all bright
21		Green laser
	000-015	no stroboscopic
	016-249	speed from slow to fast
	250-255	all bright
22		Macro Function
	000-050	no function
	051-150	random voice control
	151-250	self-propelled (from slow to fast)
	251-255	whole machine reset (the value stays for 3 seconds and takes effect)