

FS600LED 3 Channel - DMX Values & Functions		
Channel	Value	Function
1	0 - 255	MASTER DIMMER 0% - 100%
2	0 - 31 32 - 63 64 - 95 96 - 127 128 - 159 160 - 191 192 - 223 224 - 255	COLOR WHITE RED YELLOW BLUE GREEN ORANGE UV WARM WHITE
3	0 - 15 16 - 131 132 - 139 140 - 181 182 - 189 190 - 231 232 - 239 240 - 247 248 - 255	STROBING NO FUNCTION STROBING SLOW - FAST NO FUNCTION SLOW OPEN - FAST CLOSE NO FUNCTION SLOW CLOSE - FAST OPEN NO FUNCTION RANDOM STROBE NO FUNCTION

Please notice that the DMX Address is fixed on address 001 !

If you need another start address, please specify this with your purchase order