

ELIMINATOR LP 8R - DMX TRAITS

CHANNEL				DMX VALUES	FUNCTION	LEDS
3Ch	6Ch	13Ch	38Ch			
	1	1	1	000-255	Main Dimming	Middle 7 LEDs
					Strobe / Shutter	
				000-031	Shutter Closed (LEDs OFF)	
				032-063	Shutter OPEN (LEDS ON)	
				064-095	Strobe effect slow to fast	
		2	2	096-127	Shutter OPEN(LEDS ON)	
				128-159	Pulse effect in sequences	
				160-191	Shutter OPEN(LEDS ON)	
				192-223	Random strobe effect slow to fast	
				224-255	Shutter OPEN(LEDS ON)	
	2		3	000-255	Color macro function , from dark to bright	
		3	4	000-255	Red dimming , from dark to bright	
		4	5	000-255	Green dimming , from dark to bright	
		5	6	000-255	Blue dimming , from dark to bright	
		6	7	000-255	White dimming , from dark to bright	
	3	7	8	000-255	Main dimming	LED Strip
					Strobe / Shutter	
				000-031	Shutter Closed (LEDs OFF)	
				032-063	Shutter OPEN (LEDS ON)	
				064-095	Strobe effect slow to fast	
		2	2	096-127	Shutter OPEN(LEDS ON)	
				128-159	Pulse effect in sequences	
				160-191	Shutter OPEN(LEDS ON)	
				192-223	Random strobe effect slow to fast	
				224-255	Shutter OPEN(LEDS ON)	
2	4		10	000-255	Color macro function	
	5		11	000-255	Macro function auto-run	
	6		12	000-255	Macro function auto-run speed , Slow to Fast	
		9	13	000-255	Red 1 dimming , from dark to bright	
		10	14	000-255	Green 1 dimming , from dark to bright	
		11	15	000-255	Blue 1 dimming , from dark to bright	
			16	000-255	Red 2 dimming , from dark to bright	
			17	000-255	Green 2 dimming , from dark to bright	
			18	000-255	Blue 2 dimming , from dark to bright	
			19	000-255	Red 3 dimming , from dark to bright	
			20	000-255	Green 3 dimming , from dark to bright	
			21	000-255	Blue 3 dimming , from dark to bright	
			22	000-255	Red 4 dimming , from dark to bright	
			23	000-255	Green 4 dimming , from dark to bright	
			24	000-255	Blue 4 dimming , from dark to bright	
			25	000-255	Red 5 dimming , from dark to bright	
			26	000-255	Green 5 dimming , from dark to bright	
			27	000-255	Blue 5 dimming , from dark to bright	

DMX TRAITS

CHANNEL				DMX VALUES	FUNCTION	
3Ch	6Ch	13Ch	38Ch			
			28	000-255	Red 6 dimming , from dark to bright	LED Strip
			29	000-255	Green 6 dimming , from dark to bright	
			30	000-255	Blue 6 dimming , from dark to bright	
			31	000-255	Red 7 dimming , from dark to bright	
			32	000-255	Green 7 dimming , from dark to bright	
			33	000-255	Blue 7 dimming , from dark to bright	
			34	000-255	Red 8 dimming , from dark to bright	
			35	000-255	Green 8 dimming , from dark to bright	
			36	000-255	Blue 8 dimming , from dark to bright	
1		12	37		Auto Run	
				000-029	Empty , No Function	
				030-054	Auto run 1 , Color fade-in and fade-out (3 colors: red, green, and blue)	
				055-079	Auto run 2 , Color fade-in and fade-out (7 colors: red, green, blue, cyan, magenta, yellow, and white)	
				080-104	Auto run 3 , Color dimming	
				105-129	Auto run 4 , Red fade-in and fade-out	
				130-154	Auto run 5 , Green fade-in and fade-out	
				155-179	Auto run 6 , Blue fade-in and fade-out	
				180-204	Auto run 7 , White fade-in and fade-out	
				205-229	Auto run 8 , Color changes (3 colors: red, green, and blue)	
				230-255	Auto run 9 , Color changes (7 colors: red, green, blue, cyan, magenta, yellow, and white)	
3		13	38	000-255	Speed / Sound sensitivity , Speed adjustment (when sound control is off) / Sound control sensitivity (when sound control is on)	